

Farenhyt

IFP-100

IFP-100 is an intelligent analog/addressable fire control panel. The basic IFP-100 system has a single SLC loop and four notification appliance circuits that can be programmed for notification outputs or auxiliary power. IFP-100 also has a built-in dual line digital fire communicator, Form C trouble relay, and two programmable Form C relays. The firmware has powerful features, such as detector sensitivity, day/night thresholds, drift compensation and pre-trouble maintenance alert.

IFP-100 supports a variety of other devices that can be added to the system such as RA-100 remote annunciator, 5824 serial/parallel printer interface module (for printing system reports), and 5496 intelligent power module, and Hochiki or Intelligent Device Protocol (IDP) devices.

Features

- Built-in support for up to 127 Hochiki devices or 99 IDP detectors and 99 IDP modules
- Uses standard wire—no shielded or twisted pair required
- Built-in digital communicator for remote reporting of system activity and system programming
- Central station reporting by point or by zone
- Jumpstart® auto-programming
- Supports Class B (Style 4) and Class A (Style 6 or Style 7) configuration for SLC
- Distributed, intelligent power
- Built-in synchronization for AMSECO, Gentex®, Faraday, System Sensor®, and Wheelock® appliances
- Sensor sensitivity settings and day/night sensitivity setting
- Automatic drift compensation
- Notification circuits configurable as 2 Class A (Style Z), 4 Class B (Style Y), or auxiliary power for resettable, constant, or door holder power
- Built-in annunciator with a backlit 80-character LCD display
- RS-485 bus provides communication to system accessories
- Built-in Form C trouble relay rated at 2.5 amps at 27.4 VDC
- Two built-in Form C programmable relays rated at 2.5 amps at 27.4 VDC
- SLC device locator can be used to locate a single or multiple devices on a SLC loop
- System automatically performs detector sensitivity test
- 13 preset notification cadence patterns (including ANSI 3.41) and four user programmable patterns
- Built-in RS-232 and USB interface for programming
- Upload or download programming, event history, or detector status onsite or from a remote location using a PC and 5650/5651 Silent Knight Software Suite (SKSS)
- Improvements in SKSS deliver five times faster upload/downloads
- Non volatile event history stores up to 1000 events
- 125 Software zones and 125 output groups

Single Loop Analog/Addressable
Fire Alarm Control System



MEA

429-92-E Vol. XIV



IFP-100

- 6 amp power supply and maximum charging capacity of 35 amp hours (An additional cabinet enclosure is required for batteries in excess of 18 amp hours)
- Integrated dead front panel protects operator from exposure to electrical components
- The FACP enclosure features a Plexiglass® viewing window to protect annunciator
- Programmable to automatically display oldest event first or display tally of system events
- Acknowledge function allows operator to keep track of event status
- Programmable date setting for Daylight Saving Time

Installation

The IFP-100 can be surface or flush mounted.



**SILENT
KNIGHT**

by Honeywell

7550 Meridian Circle
Maple Grove, Mn 55369-4927
763-493-6455
1-800-328-0103
Fax: 763-493-7475
<http://www.farenhyt.com>

P/N 350388 Rev E 04/21/06
Copyright © 2006 Silent Knight
Jumpstart® is a Registered Trademark of
Silent Knight

Compatibility

The IFP-100 SLC supports multiple device types of the *same* protocol:

- Hochiki
- IDP

You cannot mix Hochiki and IDP devices on a FACP. However, any combination of addressable devices of the same protocol can be used on the IFP-100.

See Hochiki Devices specification sheet (PN 350360) and IDP Device Protocol Devices specification sheet (PN 350361) for more information.

Specifications

Physical

Flush Mount Dimensions: 14.5"W x 24.75"H x 3.5"D
(36.8 W x 62.9 H x 8.73 D cm)

Overall Dimensions: 16"W x 26.4"H x 4.65"D
(40.6 W x 67 H x 11.8 D cm)

Weight: 28 lbs. (12.8 kg)

Color: Red

Environmental

Operating Temperature: 32°F – 120°F (0°C – 49°C)

Humidity: 10% – 93% non-condensing

Electrical

Primary AC: 120 VRMS @ 50/60 Hz, 2.5A

Total Accessory Load: 6A @ 27.4 VDC power-limited

Standby Current: 170 mA

Alarm Current: 325 mA

Battery Charging Capacity: 7 to 35 AH

Battery Size: 18 AH max. allowed in control panel cabinet. Larger capacity batteries can be housed in RBB accessory cabinet.

Notification Appliance Circuits

Four circuits that can be programmed individually as:
Notification Circuits: 3A per circuit @ 27.4 VDC, power-limited
Auxiliary Power Circuits: 3A per circuit @ 27.4 VDC, power-limited

Indicator Lights

Alarm (Red): Flashes when in alarm; solid when alarm silenced

Supervisory (Yellow): Flashes when a supervisory condition exists; solid when supervisory silenced

Trouble (Yellow): Flashes when a trouble condition exists; solid when trouble silenced

Silenced (Yellow): Solid when an alarm, trouble or supervisory condition has been silenced but not yet cleared

Power (Green): Flashes for AC failure; solid when power systems are normal

Telephone

Requirements: FCC Part 15 & Part 68 approved

Jack: RJ31X (two required)

Approvals

NFPA 13, NFPA 15, NFPA 16, NFPA 70, & NFPA 72: Central Station; Remote Signalling; Local Protective Signalling Systems; Auxiliary Protected Premises Unit; & Water Deluge Releasing Service. Suitable for automatic, manual, waterflow, sprinkler supervisory (DACT non-coded) signalling services.

Other Approvals: UL Listed; CSFM 7170-0559: 142; MEA 429-92-E Vol. XIV

Ordering Information

IFP-100 Intelligent Fire Alarm Control Panel.

SBUS Accessories

RA-100 Remote Annunciator. Same operation and similar appearance to FACP annunciator.

RA-1000R Remote Annunciator. Four line LCD annunciator with 20 characters per line. Red.

RA-1000 Remote Annunciator. Four line LCD annunciator with 20 characters per line. Gray.

RPS-1000 Intelligent Power Module.

5496 Intelligent Power Module.

5824 Serial/Parallel Printer Interface Module.

5880 LED I/O Module.

5865-3 & 5865-4 LED Fire Annunciators.

5883 Relay Interface Board.

Hochiki and IDP Devices

See the specification sheets listed below for a complete listing of the Hochiki and IDP devices.

350360 Hochiki Devices Specification Sheet.

350361 Intelligent Device Protocol Devices Specification Sheet.

Miscellaneous Accessories

5650/5651 Silent Knight Software Suite. Provides programming, upload/download, and event reporting.

5670 Silent Knight Software Suite. Provides facility monitoring.

RBB Remote Battery Box Accessory Cabinet. Use if backup batteries are too large to fit into FACP cabinet. Dimensions: 16" W x 10" H x 6" D (406 mm W x 254 mm H x 152 mm D)



This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice. For more information, contact Silent Knight 7550 Meridian Circle Suite 100, Maple Grove, Mn 55369-4927. Phone: (800) 328-0103, Fax: (763) 493-6475.



Made in the U.S.A.